


| | | | | | | | | | | | | | | | |
|-------------|------------|-----|---------------|---------------------|----|----|---|----|----|----|--|-----|--|--|--|
| 额定输入转数 | 1400 rpm | | 常用适配功率（非标可定制） | | | | <div>安装方位</div>  | | | | <div>请注意:</div> <div>1. 所有数据(PDF, CAD, 3D)变更时, 我们不做通知。</div> <div>注: 选择合适的速比和安装方位 在选择的位置打√ 如需定制可联系我司</div> | | | | |
| 最大输入转数 | 3000 rpm | | 输入孔9 | 适合功率60W-90W电机 | | | | | | | | | | | |
| 使用温度 | -5℃ - +40℃ | | 输入孔11 | 适合功率0.12KW-0.18KW电机 | | | | | | | | | | | |
| 润滑方式 | 油润滑 | | 输出孔径 | Ø14键5 | | | | | | | | | | | |
| 重量 | ≈1.2kg | | | | | | | | | | | | | | |
| 速比 | 5 | 7.5 | 10 | 15 | 20 | 25 | 30 | 40 | 50 | 60 | 80 | 100 | | | |
| 输出扭矩(N.m) | 5 | 7 | 9 | 13 | 17 | 21 | 24 | 19 | 23 | 19 | 14 | / | | | |
| 最大输出扭矩(N.m) | 10 | 14 | 18 | 26 | 34 | 42 | 48 | 38 | 46 | 38 | 28 | / | | | |

| | | | |
|------------------------------|------------|----------------------|---|
| 客户签字 Customer's Signature | | 公司名称 Company name |  |
| | | 图名 Drawing name | NMRV030-10-FA2-63B14-B3-Y-0.12-4P |
| 设计 Design | 吕云峰 | 服务热线 Service hotline | 400-8040-668 / QQ:4008040668 |
| 审核 Checked | 李东 | 网址/邮箱 Website/email | www.fht.tw / www.3fgearmotor.com fht@fht.tw / sales@3fgearmotor.com |
| 日期 Date | 2026-01-04 | 电话/传真 Tel./Fax | 021-39948832 / 021-39948836 |